

READ INSTRUCTIONS BEFORE USE

TransLite LLC
 345 Commerce Green Blvd
 Sugar Land TX 77478 USA
 +1 281 240 3111
 www.veinlite.com
 info@veinlite.com

Caution

- Veinlite PED12 is designed for external examination only.
- To avoid contamination of the device, Veinlite PED12 must be used with the disposable plastic cover.
- To avoid the spread of infection, always change the disposable plastic cover between patients and wipe the new cover with a germicidal wipe.
- These devices are intended for use only by clinicians trained in performing vascular access, or under the supervision of a clinician.
- Do not look directly into the LEDs while on.
- Device may be wiped down with a germicidal wipe.
- Do not immerse the device in liquid.
- Do not autoclave the device.

Introduction

The TransLite Veinlite PED12 is a hand-held battery-powered transillumination device for visualizing veins and superficial blood vessels in pediatric patients.

Description

The PED12 utilizes the patented¹ transillumination technique known as side-transillumination and a patented² orange color LED light. A ring of bright light from 10 orange and 4 red LEDs is aimed through a clear plastic LED Window [A] and focused below the skin surface and towards the ring's center.

The focused light creates a volume of illumination, with the central focus acting as a virtual light source under the skin. This technique achieves uniform illumination of a small region of tissue anywhere on the body.

The patented orange light is selected because of high absorption in venous blood. The red LEDs have high penetration in darkly pigmented skins. The combination of the two provides optimum imaging of veins in humans.

Vein Access

- 1 Place the Veinlite PED12 inside the disposable plastic cover so that the device is totally covered.
- 2 Place the Veinlite PED12 on the skin, with the LED Window [A] facing down. Apply gentle pressure to the Veinlite PED12 to ensure it is in contact with the skin.
- 3 Depress the Power Button [B] to turn on the orange and then the red LEDs. Use the Brightness Button [C] to control the brightness level of the device to the desired level.

- 4 To scan for veins, place Veinlite PED12 against skin perpendicular to vein direction. Scan it forward and backward. Veins will be visible as dark lines due to transillumination.
- 5 Once a suitable vein has been identified, rotate device 90°, parallel to vein.
- 6 Apply gentle pressure on the Veinlite PED12 to secure the vein.
- 7 Push back slightly on the Veinlite PED12 to stretch the skin and provide traction.
- 8 Insert the needle into the vein, through the opening of the device.

NOTE: Discard the single-use disposable plastic cover after each patient.

Power

Depressing the Power Button [B] turns on the orange LEDs. Depressing the button again, adds the red LEDs to the orange LEDs. Depressing the button again turn the unit off.

Depressing the Brightness Button [C] for one second will turn the unit off.


The LEDs will automatically shut off after 7 minutes.

Brightness Control

The Veinlite PEDI2 has three levels of brightness that are selected by pressing the Brightness Button [C] after the unit is turned on. Brightness control is important when working with small children.

Disposable Plastic Cover

The single-use disposable plastic covers for the Veinlite PEDI2 (Product #VLP2-DPC) MUST be used when the device is placed in contact with a patient's skin.



CAUTION: These plastic covers are not sterile. They should be wiped with a germicidal wipe prior to use.


Before using Veinlite PEDI2, place it inside the disposable cover with the flap on the same side as the LEDs.

Pull the flap over the device to the other side.

Wipe the LED side of the Veinlite PEDI2 and any part of it coming in contact with the patient, with a medically approved germicidal wipe.

Batteries

The Veinlite PEDI2 is powered by 2 AAA batteries. They provide between 2 and 4 hours of continuous illumination depending on the number of LEDs turned on and the brightness level used.



Low Battery Indicator

When the batteries get low, the orange lights will flicker when turned on. Replace the batteries as soon as the orange light flickers when turned on.

Installing Or Replacing Batteries

To install or replace the batteries, press firmly on the Battery Cover [D] and slide it off. Remove any used batteries. Install 2 new AAA batteries, oriented as indicated by the markings inside the battery compartment then slide the battery cover back into place.

Warranty

The Veinlite PEDI2 has a one year parts and labor warranty. It is not necessary to register your Veinlite PEDI2 for warranty. The process is automatic and the serial number of the unit provides all the information needed.

Troubleshooting

Before returning the device to TransLite for repair, please call or e-mail to obtain an authorization number and shipping details.


No refunds will be given for devices shipped without authorization.

Specifications

Number of LEDs:	10 Orange 4 Red
Weight with battery:	29g
Dimensions:	40.8x86.6x21mm
Battery:	2x AAA 1.5V

Intended Use/Indications

- Emergency venous access in infants and children.
- Venous access in infants and pediatric patients with a history of difficult venous access.
- Easier visualization of veins in dark pigmented patients.
- Easier visualization of veins in overweight infants and children.



Contraindications

- When used for internal examination
- When used without the disposable plastic cover

Explanation of Symbols

- Model Number
- Serial Number
- Manufacturer
- EC Representative (EU Only)
- Do not dispose of as unsorted municipal waste

M. Devices Group
Health Education Centre
The Church, Portland Street
Southport PR8 1HU
United Kingdom
+44 1704 544 944

¹ US Patent Number 5,146,923

² US Patent Number 7,874,698

©2019 TransLite, LLC. All rights reserved. These instructions or any part thereof may not be reproduced by any means, without prior permission of TransLite, LLC.



Made in USA

VLP2-DFU Rev. A.0220